

# KENWOOD

Listen to the Future

## NX-700/800

### NEXEDGE®

NEXEDGE® VHF/UHF Digital & FM Mobile Radios

**NXDN®**

**FleetSync®**  
by KENWOOD

#### ● GENERAL FEATURES

- 30W (136-174, 400-470 MHz) Models
- 512 CH-GID / 128 Zones
- Dash & Remote Mount
- 14 Character Alphanumeric Aliases
- Backlit Dot Matrix LCD
- Function/Status LCD Icons
- Multi-Language Display
- Date & 12/24 Hour Time Clock
- Transmit/Busy/Call Alert/Warn LED
- On/Off Power Control
- 4 Up/Down Selectors
- 6 Front PF Keys
- Emergency/AUX Key
- 4W Speaker Audio
- DB-25 Accessory Connector
- 9 Programmable AUX I/Os
- 2 Programmable AUX Outputs
- KPG-111D Windows® FPU
- Flash Firmware Upgrading
- MIL-STD-810 C/D/E/F/G
- IP-54/55 Water & Dust Intrusion
- PC Serial Interface
- SDM Manual Input<sup>1</sup>
- Transparent Data Mode<sup>1</sup>
- GPS Receiver Option
- VGS-1 Voice Guide / Voice & GPS Data Storage Option

#### ● DIGITAL – COMMON

- NXDN® Digital Air Interface
- AMBE+2™ VOCODER
- 6.25 & 12.5 kHz Channels
- Over-the-Air Alias
- Over-the-Air Programming
- Paging Call
- Emergency Call
- All Group Call
- Status Messaging<sup>1</sup>
- Remote Stun/Kill<sup>1</sup>
- Remote Check<sup>1</sup>
- Short & Long Data Messages<sup>1</sup>
- GPS Location with Voice<sup>1</sup>
- NXDN® Scrambler Included

#### ● DIGITAL CONVENTIONAL MODE

- 64 Radio Access Numbers (RAN)
- Individual & Group Selective Call
- Mixed FM/Digital Operation
- Conventional IP Networks
- Site Roaming

#### ● DIGITAL TRUNKING MODE

- Individual Private Call
- Group Call & Broadcast Call
- Transmission Trunked Mode<sup>2</sup>
- Message Trunked Mode<sup>2</sup>
- Call Queuing with Priority<sup>2</sup>
- Late Entry (UID & GID)<sup>2</sup>
- 4 Priority Monitor ID's<sup>2</sup>
- Remote Group Add<sup>1</sup>
- Failsafe Mode

#### ● MULTI-SITE IP NETWORKS COMPATIBLE

- Individual Private Call
- Group Call & Broadcast Call
- Transmission Trunked Mode<sup>2</sup>

#### ● SCAN

- Single Zone / Multi-Zone / List Scan
- Dual Priority Scan (Conventional)




## Options

**KMC-35**  
Microphone



**VGS-1**  
Voice Guide  
& Storage Unit



**KAP-2**  
Horn Alert  
/ PA Relay Unit



**KCT-46**  
Ignition Sense Cable



**KMC-36**  
Microphone  
with Keypad




**KRK-10**  
Panel Remote Kit



**KCT-23M**  
DC Cable (10 feet)



**KMB-10**  
Key Lock Adapter



**KMC-9C**  
Control Station  
Desktop Microphone



**KPS-15**  
DC Power Supply



**KCT-23M3**  
DC Cable (23 feet)

KCT-23M3

**KLF-2**  
Line Noise Filter



## Main Specifications

All accessories and options may not be available in all markets. Contact an authorized Kenwood dealer for details and complete list of all accessories and options.

		NX-700 K	NX-800 K
<b>GENERAL</b>			
<b>Frequency Range</b>	Type 1	136-174 MHz	
	Type 2		400-470 MHz
<b>Number of Channels</b>			512
<b>Zones</b>			128
<b>Max. Channels per Zone</b>			250
<b>Channel Spacing</b>	<b>Analog</b>	12.5 / 15 / 25 / 30 kHz	12.5 / 25 kHz
	<b>Digital</b>	6.25 / 12.5 kHz	6.25 / 12.5 kHz
<b>Operating Voltage</b>		13.6 V DC $\pm$ 15%	
<b>Operating Temperature Range</b>		-22° F to +140° F (-30° C to +60° C)	
<b>Frequency Stability</b>		$\pm$ 2.0 ppm	$\pm$ 1.0 ppm
<b>Antenna Impedance</b>		50 $\Omega$	
<b>Dimensions (W x H x D)</b>	Projections not included	6.30 x 1.77 x 6.18 in (160 x 45 x 157 mm)	
<b>Weight (net)</b>		3.04 lb (1.38 kg)	
<b>FCC ID</b>	<b>K</b> Type 1	K44378600	
	<b>K</b> Type 2		K44378701
<b>IC Certification</b>	<b>K</b> Type 1	282F-378600	
	<b>K</b> Type 2		282F-378701

Analog measurements made per TIA/EIA 603 and specifications shown are typical. Kenwood reserves the right to change specifications without prior notice or obligation.

FleetSync® is a registered trademark of Kenwood Corporation.  
LTR® is a registered trademark of Transcript International.  
AMBE+2™ is a trademark of Digital Voice Systems Inc.  
Windows® is a registered trademark of Microsoft Corporation.  
NXDN® is a trademark of Kenwood Corporation and Icom Inc.  
NEXEDGE® is a trademark of Kenwood Corporation.

		NX-700 K	NX-800 K
<b>RECEIVER</b>			
<b>Sensitivity</b>	<b>Digital @ 6.25 kHz (3% BER)</b>		0.20 $\mu$ V
	<b>Digital @ 12.5 kHz (3% BER)</b>		0.28 $\mu$ V
	<b>Analog (12 dB SINAD)</b>		0.25 $\mu$ V
<b>Selectivity</b>	<b>Analog @ 25 kHz</b>		80 dB
	<b>Analog @ 12.5 kHz</b>		70 dB
<b>Intermodulation</b>	<b>Analog</b>	75 dB ( $\pm$ 50,100 kHz)	
<b>Spurious Response</b>	<b>Analog</b>	90 dB	85 dB
<b>Audio Distortion</b>		Less than 3%	
<b>Audio Output</b>		4 W / 4 $\Omega$	
<b>TRANSMITTER</b>			
<b>RF Power Output</b>		30 W to 1 W	30 W to 1 W
<b>Spurious Response</b>		73 dB	75 dB
<b>FM Hum &amp; Noise</b>	<b>Analog @ 25 kHz</b>		50 dB
	<b>Analog @ 12.5 kHz</b>		45 dB
<b>Audio Distortion</b>		Less than 3%	
<b>Modulation</b>		16K0F3E, 14K4F1D, 11K0F3E, 8K10F1D, 8K10F1E, 8K30F1E, 8K30F1D, 8K30F7W, 4K00F1E, 4K00F1D, 4K00F7W, 4K00F2D	

footnotes from Front:

<sup>1</sup> Requires NX subscriber unit PC Serial Interface compatible software application (e.g. Kenwood AVL & Dispatch Messaging software) or hardware (e.g. console).  
<sup>2</sup> These trunked features are primarily system programming and operational dependent. Priority Monitor also requires NX subscriber settings.

## Applicable MIL-STD & IP

MIL Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
<b>Low Pressure</b>	500.1/Procedure I	500.2/Procedure I, II	500.3/Procedure I, II	500.4/Procedure I, II	500.5/Procedure I, II
<b>High Temperature</b>	501.1/Procedure I, II	501.2/Procedure I, II	501.3/Procedure I, II	501.4/Procedure I, II	501.5/Procedure I, II
<b>Low Temperature</b>	502.1/Procedure I	502.2/Procedure I, II	502.3/Procedure I, II	502.4/Procedure I, II	502.5/Procedure I, II
<b>Temperature Shock</b>	503.1/Procedure I	503.2/Procedure I	503.3/Procedure I	503.4/Procedure I, II	503.5/Procedure I
<b>Solar Radiation</b>	505.1/Procedure I	505.2/Procedure I	505.3/Procedure I	505.4/Procedure I	505.5/Procedure I
<b>Rain</b>	506.1/Procedure I, II	506.2/Procedure I, II	506.3/Procedure I, II	506.4/Procedure I, III	506.5/Procedure I, III
<b>Humidity</b>	507.1/Procedure I, II	507.2/Procedure II, III	507.3/Procedure II, III	507.4	507.5/Procedure II
<b>Salt Fog</b>	509.1/Procedure I	509.2/Procedure I	509.3/Procedure I	509.4	509.5
<b>Dust</b>	510.1/Procedure I	510.2/Procedure I	510.3/Procedure I	510.4/Procedure I, III	510.5/Procedure I
<b>Vibration</b>	514.2/Procedure VIII, X	514.3/Procedure I	514.4/Procedure I	514.5/Procedure I	514.6/Procedure I
<b>Shock</b>	516.2/Procedure I, II, V	516.3/Procedure I, IV	516.4/Procedure I, IV	516.5/Procedure I, IV	516.6/Procedure I, IV
<b>International Protection Standard</b>					
<b>Dust &amp; Water Protection</b>	IP54: Radio itself IP54/55: Remote head with KRK-10				

## Listen to the Future

Kenwood has always connected with people through sound. Now we want to expand the world of sound in ways that only Kenwood can, listening to our customers and to the pulse of the coming age as we head toward a future of shared discovery, inspiration and enjoyment.

Kenwood Electronics Canada Inc.  
Canadian Headquarters and Distribution  
6070 Kestrel Road, Mississauga, Ontario, Canada L5T 1S8

  
www.kenwood.ca

